

Setting	JSON identifier	Value type	Valid values	Note
Flip video	selfViewMirror	bool	true/false	
Do not show self-view when the camera is turned off in the application	disableSelfViewOnBlind	bool	true/false	
Invert X-axis PTZ camera control	invertedPTZControl	bool	true/false	
Speaker volume	audioPlayLevel	double	[0; 1]	Don't use with Automatic gain control
Microphone volume	audioCapturerLevel			
Echo cancellation	aecEnable	bool	true/false	
Automatic gain control	agcEnable	bool	true/false	
Noise suppression	noiseSupEnable	bool	true/false	
Enable diagnostic audio dump	audioDumpEnable	bool	true/false	
Control app with HID device buttons	isSpeakerphoneHardware Muted	bool	true/false	
Connection server	userDefinedServerHost	string		

Server connection port	userDefinedServerPort	int		
Server connection	corporateServer	bool	true	Connection to a corporate server, which is specified in <b>userDefinedServerHost</b> parameter
			false	Connection to TCO, this parameter is ignored if <b>userDefinedServerHost</b> is specified
Suppress direct server connection	forbidDirectConnection	bool	true/false	
Check for available server connections upon launch	canAskForServerSelector	bool	true/false	
Use proxy system settings	useSystemProxy	bool	true/false	
User limits	userDefinedBitrate	int	0	User bitrate
			1	Modem
			2	ADSL
			3	Wi-Fi
			4	Ethernet
			5	Maximum

Input bitrate	inputBandWidth	int	[32, 10240]	These settings should be used simultaneously while the parameter <b>userDefinedBitrate</b> should be either left unspecified or set to 0.
Output bitrate	outputBandWidth	int		
Upload limits	uploadLimit	int	[1; 100]	
Download limits	downloadLimit	int		
Sign in automatically	enableAutologin	bool	true/false	
Allow the “Rate application” pop-up to be displayed	canAskForRateUs	bool	true/false	When enabled, the rating window won’t be displayed after calls/conferences
Language	language	string	ru	Russian
			en	English
			de	German
			it	Italian
			cs	Czech
			es	Spanish
			fr	French
			pl	Polish

			tr	Turkish
			pt	Portuguese
			az	Azerbaijani
			uk	Ukrainian
			zht	Chinese (Traditional)
			zh	Chinese (Simplified)
			vi	Vietnamese
			ko	Korean
			ja	Japanese
			he	Hebrew
			ar	Arabic
Hide camera error messages	cameraErrorsHidden	bool	true/false	When parameter is enabled, an icon indicating a camera error will be displayed. Clicking on this icon will expand the error message.
Automatically hide the names of idle conference participants	hideDnByTimeout	bool	true/false	

Minimize app to the tray when closing	leaveAppRunningInTray	bool	true/false	
Launch automatically at system startup	enableAutoStart	bool	true/false	
Minimal rate of video area render update	minRenderFrameRate	int	[0; 60]	The minimal rate should not exceed the maximal rate
Maximal rate of video area render update	maxRenderFrameRate	int	[0; 60]	The maximum rate should not be lower than the minimum rate